

<b>Technical Guidance</b>			Creator	Confirmer	Approver
(PaX-i3D Guide for Defect Prevention of AnyGrabber Card 5)					
Creator	Eunice Lyou	Doc. No.	GCS-TECH-20140114B-ENG		
To		Cc			
Object	PaX-i3D	Category	AnyGrabber Card		
Subject	PaX-i3D Guide for Defect Prevention of AnyGrabber Card 5				

**Revision History**

Date	Revision	Editor	Comments
2014.01.14	0.0	Augustine Jeon	Created
2014.01.14	0.0	Augustine Jeon	Conversion
2014.01.22	0.0	Eunice Lyou	Conversion Revised

# Contents

- 1 General Provision.....2**
  - 1.1 Objective .....2
  - 1.2 Application Scope.....2
  
- 2 Description .....2**
  - 2.1 Symptom .....2
  - 2.2 Version Information .....2
  
- 3 Work Process .....2**
  - 3.1 Update of the Driver of AnyGrabber Card 5.....2
  
- 4 Attachments.....5**

# 1 General Provision

## 1.1 Objective

- This is to provide the guide for defect prevention of AnyGrabber Card 5 of PaX-i3D.

## 1.2 Application Scope

- Model : PaX-i3D
- S/N: Applicable for the product released before S/N 052-0875

# 2 Description

## 2.1 Symptom

- 1) PC reboots after the occurrence of the blue screen in PC screen when selecting the ready button in capture software.

## 2.2 Version Information


- 1) Version Information of Driver

Classification	Before Modification	After Modification
AG50 Driver	V 1.0.3.4	V 1.0.3.5

# 3 Work Process

## 3.1 Update of the Driver of AnyGrabber Card 5


- 1) Uninstall the AnyGrabber3 N1000(x64) at the Device Manger → Imaging devices tab.




2) Check on the check box of “Delete the driver software for this device” and press OK.




3) Multimedia Controller” is searched automatically at the ‘Other devices tab’ of Device Manager.




4) Move to Control Panel → Program → Programs and Features and uninstall the “AnyGrabber3(5)(x64)”.




- 5) After unzipping the " Frame\_Grabber\_AG5.zip" file, move to the Driver tab and select the system type according to the customer's system.




- ① In case of system with 32bits




- ② In case of system with 64bits





- 6) Proceed the installation followed by Install Shield Wizard.





System must be rebooted after installing the Driver.

7) Confirm the Image device installation and check the version of AnyGrabber Card 5.



#### 4 Attachments

- 1) Frame\_Grabber\_AG5.zip
- 2) PaX-i3D AG50 Driver Issue List.xlsx